

# SN- HW045 LED Portable Emergency Camping Light

- UL, RoHS and FCC listed
- Highlight 2835 LED
- Lightweight design of product
- Easy to carry
- LM 80 light source, low luminous decay, long life, 3 years warranty

The fourth gear is warning system, 1 second 3 flashes, can be used for calling for help, warning and so on.



## Specifications

| Model No.         | SN-HW045  |         |         |          |
|-------------------|---|---------|---------|----------|
| Battery           | Lithium Battery                                     |         |         |          |
| AC Charger        | INPUT: 100V-240VAC 2.0A 50-60Hz<br>OUTPUT: DC18V-5A |         |         |          |
| Power             | Low   | Mid     | High    | Flashing |
|                   | 9W  | 17W     | 25W     |          |
| Lumens            | 900LM   | 1600LM  | 2200LM  |          |
| Efficacy          | 100LM/W   | 95LM/W  | 88LM/W  |          |
| Battery Work Time | 9 hours   | 5 hours | 3 hours | 20 hours |
| LED Model         | SMD2835   |         |         |          |
| LED Quantity      | 288PCS  |         |         |          |
| CCT               | 3000K,4000K,5000K,6500K                             |         |         |          |
| Lifespan          | 30,000 Hours  |         |         |          |
| Tripod            | Height:1.5M(Optional)                               |         |         |          |
| Beam Angle        | 360°  |         |         |          |
| Ambient Temp.     | -40°-122°F  |         |         |          |
| Warranty          | 3 years   |         |         |          |
| IP Rating         | IP 65   |         |         |          |
| Certificates      | UL,FCC,ROHS   |         |         |          |
| Product Size      | 117*117*222mm                                       |         |         |          |
| N.W.              | 1.9KGS(With Tripod is 3.5KGS)                       |         |         |          |



## Components

- 1.LED Light Module
- 2.AC Charger
- 3.Tripod,360° Turn, Max Height:5 feet



## LED Display

- ①.Discharge Gear (Total:4 Gears)
- ②.Battery Indicator
- ③.Charging mode
- ④.Battery available time

